



R&R Video-Signal-Converter RR-P-470

Power supply size	+/- 5 volts DC +/- 5% 38.1mm x 28.575 mm
Input	4 x asymmetric, 10pin FDC-header
Output	4 x symmetric, 15pin male D-Sub
variant 1	ch# 1,2 for audio in 100kohms asymmetric, out 680ohms symmetric ch# 3,4 for video in 75ohms asymmetric, out 100ohms symmetric
variant 2	4 channels for video in 75ohms asymmetric, out 100ohms symmetric
variant 3	4 channels for audio in 100kohms asymmetric, out 680ohms symmetric
Drawing	DNR 16804

P2: unbalanced, asymmetric outputs			
signal	pin		signal
GND	1	2	1 asym
GND	3	4	2 asym
GND	5	6	
GND	7	8	3 asym
GND	9	10	4 asym

P1: balanced, symmetric outputs 15pin D-sub male			
signal	pin		signal
1 sym+	1	9	GND
1 sym-	2	10	GND
2 sym+	3	11	GND
2 sym-	4	12	GND
3 sym+	5	13	GND
3 sym-	6	14	GND
4 sym+	7	15	GND
4 sym-	8		

P3,P4: power	
signal	pin
-5V DC	1
GND	2
GND	3
+5V DC	4